

# Bally / Stern Rectifier Board

Playfield									Cabinet											
J1	1	2	3	4	5	6	7	8	9	J2	1	2	3	4	5	6	7	8	9	10
	WHITE	GREEN			ORANGE	BROWN	BLUE	RED		YEL-BLK	GREEN			GR-RED	YELLOW	BLUE		ORANGE	GREEN	
	GEN ILL. RET.	GEN ILL. RET.	SPARE	KEY	GEN ILL. BUSS	SOL. BUSS	SW. ILL. BUSS	GEN ILL. BUSS	SW. ILL. BUSS	GEN. ILL. BUSS	SOL. BUSS	SPARE	SPARE GND.	GEN ILL. RET.	SW. AC POWER	AC RET.	KEY	FLIP. SW. RET.	PWR. LINE GND.	
	GND	GND			7.3VAC	43VDC	5.4VDC	7.3VAC	5.4VDC *	7.3VAC	43VDC			GND	120VAC	120VAC		GND	GND	

\* Used only on the AS2518-49 rec. board

Backbox																				
J3	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
	GREEN	WHITE	RED-BLK	WHT-RED	GRY-BLU	BLU		ORANGE	YELLOW	ORANGE	RED	GRAY	WHT-YEL	WHT-BLK	WHT-BLU	BLK-BLU	WHT-BRN	WHITE	RED-YEL	WHT-ORG
	GEN ILL. RET.	GEN ILL. RET.	SW. LAMP RET.	SW. LAMP RET.	TO SDB (190V) INPUT	SW. ILL. BUSS	KEY	TO SDB (+5V) INPUT	RELAY (43V)	GEN ILL. BUSS	GEN. ILL. BUSS	Z. C. INPUT	SOL. BUSS	SW. LAMP RET.	TO SDB (+5V) RET.	TO SDB (190V) RET	TO SDB (+5 FILT.) RET	TO SDB (190V FILT.) RET.	SOL. RET. BUSS	SOL. RET. BUSS
	GND	GND	GND	GND	230VDC	5.4VDC		11.9VAC	43VDC	7.3VAC	7.3VAC	43VDC	43VDC	GND	GND	GND	GND	GND	GND	GND